

STELLA-1 Alt Display Wiring List

Line	Function	Location 1	Location 2	color	done
1	IM0	Display Rear	DO NOT close jumper		<input type="checkbox"/>
2	IM1	Display Rear	Close Jumper		<input type="checkbox"/>
3	IM2	Display Rear	Close Jumper		<input type="checkbox"/>
4	IM3	Display Rear	Close Jumper		<input type="checkbox"/>
5	+3.3 V	Feather 3V	Display VIN		<input type="checkbox"/>
6	+3.3 V	Feather 3V	Touch Controller VIN		<input type="checkbox"/>
7	GND	Feather GND	Display GND		<input type="checkbox"/>
8	GND	Feather GND	Touch Controller GND		<input type="checkbox"/>
9	SPI SCK	Feather SCK	Display CLK		<input type="checkbox"/>
10	SPI MOSI	Feather MOSI	Display MOSI		<input type="checkbox"/>
11	SPI MISO	Feather MISO	Display MISO		<input type="checkbox"/>
12	Display Reset	Feather D4	Display RST		<input type="checkbox"/>
13	i2c SDA	Feather SDA	Touch Controller SDA		<input type="checkbox"/>
14	i2c SCL	Feather SCL	Touch Controller SCL		<input type="checkbox"/>
15	Display CS	Feather 9	Display CS		<input type="checkbox"/>
16	Display D/C	Feather 10	Display D/C		<input type="checkbox"/>
17	Touch X+	Display X+	Touch Controller X+		<input type="checkbox"/>
18	Touch Y+	Display Y+	Touch Controller Y+		<input type="checkbox"/>
19	Touch X-	Display X-	Touch Controller X-		<input type="checkbox"/>
20	Touch Y-	Display Y-	Touch Controller Y-		<input type="checkbox"/>